Geno-Sen's

Streptococcous Pneumonia (Rotor Gene)

Real Time PCR Kit

Quantitative

for use with the

Rotor Gene™ 2000/3000/6000


(Corbett Research Australia)



PACK INSERT

Revised JULY 2016

Genome Diagnostics Pvt. Ltd. (An ISO 13485:2012, 9001:2008 Certified Company)



Genome Diagnostics Pvt. Ltd Up Mohal Naryal, Khasra No. 427, Old Timber Depot Road, Parwanoo, Dist Solan Himachal Pradesh 173220 Ph: +91 9810037653 Fax: 01792-234286 Email: genome24@rediffmail.com

EMERGO EUROPE Prinsessegracht 20,2514 AP, The Hague The Netherlands Table of Contents

1.	Contents of Kit.						
2.	Storage of the kit.						
3.	Streptococcus Pneumonia information	Page 4					
4.	Precautions for PCR	Page 5					
5.	Additionally required Materials & Devices	Page 5					
6.	Principle of Real Time PCR	Page 6					
7.	Description of the Product.	Page 6					
8.	Procedure	Page 6					
	 8.a DNA Extraction 8.b Inhibition Control 8.c Quantitation 8.d Preparation for PCR 8.e Preparation for PCR amplification 8.f Programming of the Rotor Gene 2000/3000 8.g Programming of the Rotor Gene 6000 	Page 6 Page 7 Page 8 Page 9 Page 9 Page 10 Page 18					
9.	a) Generated Data Interpretation & Analysis 2000/3000 b) Generated Data Interpretation & Analysis 6000	Page 27 Page 29					
10.	a) Trouble shooting 2000/3000 b) Trouble shooting 6000	Page 31 Page 31					
11.	Specifications 11.a Sensitivity & Reproducibility 11.b Specificity	Page 32 Page 33					
12.	Warranty	Page 34					
13.	Limitations of product use.	Page 34					
14.	List of GENO-SEN'S range of Real Time PCR kits						

Streptococcous Pneumonia Geno-Sen's Real Time PCR Kit for use with the Rotor

Gene[™] 2000/3000/6000^{*} (Corbett Research).

1. Contents of the Kit:

Color	Contents	REF 9111310	REF 9111311	REF 9111312
Code		100 rxns	50 rxns	25 rxns
R1	Streptococcous	25 rxns x 4 Vials	25 rxns x 2	25 rxns x 1 Vials
Blue	Pneumonia Super		Vials	
	mix.			
R2 <mark>Yellow</mark>	Mg Sol RT.	1 Vial	1 Vial	1 Vial
S.	Streptococcous	1 Vial of 300µl	1 Vial of 300µl	1 Vial of 300µl
Pneumo	Pneumonia			
S1 Red	Standard 1			
Reu	1 X 10 ⁵ copies/µl			
S.	Streptococcous	1 Vial of 300µl	1 Vial of 300µl	1 Vial of 300µl
Pneumo	Pneumonia			
S2 Red	Standard 2			
Reu	1 X 10 ⁴ copies/µl			
S.	Streptococcous	1 Vial of 300µl	1 Vial of 300µl	1 Vial of 300µl
Pneumo	Pneumonia			
S3 Red	Standard 3			
Reu	1 X 10 ³ copies/µl			
S.	Streptococcous	1 Vial of 300µl	1 Vial of 300µl	1 Vial of 300µl
Pneumo	Pneumonia			
S4 Red	Standard 4			
Reu	1 X 10 ² copies/µl			
S.	Streptococcous	1 Vial of 300µl	1 Vial of 300µl	1 Vial of 300µl
Pneumo	Pneumonia			
S5 Red	Standard 5			
Red	1 X 10 ¹ copies/µl			
W	Molecular Grade	1 Vials of 1 ml	1 Vial of 1 ml	1 Vial of 1 ml
White	Water.			
IC-1 (R3) Green	IC-1 RG (R3)	1 Vial of 1 ml	1 Vial of 1 ml	1 Vial of 1 ml

R = Reagents

S = Quantitation Standards

W = Molecular Grade Water.

All Vials have Color Coder tops to distinguish between different reagents.

^{*} The Rotor Gene™ 2000/3000/6000 is a registered trademark of Corbett Research, Australia.

2. Storage of the Kit.

All the reagents of the kit should be stored at -20°C and is stable till expiry at this temperature. Repeated thawing and freezing (> 3x) should be avoided, as this may reduce the sensitivity of the assay. If the kit is to be used only occasionally, the reagents should be frozen in aliquots. Storage at +4°C is not recommended & should not exceed a period of 2 hours in any case.

3. Streptococcous Pneumonia Information

Application

Pneumococcal disease are infections caused by the bacteria Streptococcus pneumoniae, also known as pneumococcus. The most common types of infections caused by this bacteria include middle ear infections, pneumonia, blood stream infections (bacteremia), sinus infections, and meningitis. Young children are much more likely than older children and adults to get pneumococcal disease. Children under 2, children in group child care, and children who have certain illnesses (for example sickle cell disease, HIV infection, chronic heart or lung conditions) are at higher risk than other children to get pneumococcal disease. In addition, pneumococcal disease is more common among children of certain racial or ethnic groups, such as Alaska Natives, Native Americans, and African-Americans, than among other groups. Streptococcus pneumoniae is the most common cause of bacteremia, pneumonia, meningitis and otitis media in young children.

High fever, headache, and stiff neck are common symptoms of meningitis in anyone over the age of 2 years. These symptoms can develop over several hours, or they may take 1 to 2 days. Other symptoms may include nausea, vomiting, discomfort looking into bright lights, confusion, and sleepiness. In newborns and small infants, the classic symptoms of fever, headache, and neck stiffness may be absent or difficult to detect, and the infant may only appear slow or inactive, or be irritable, have vomiting, or be feeding poorly.

In adults, pneumococcal pneumonia is often characterized by sudden onset of illness with symptoms including shaking chills, fever, shortness of breath or rapid breathing, pain in the chest that is worsened by breathing deeply, and a productive cough. In infants and young children, signs and symptoms may not be specific, and may include fever, cough, rapid breathing or grunting.

Meningitis is the most severe type of pneumococcal disease. Of children under 5 years with pneumococcal meningitis, about 5% will die of their infection and others may have long-term problems such as hearing loss. Many children with pneumococcal pneumonia or blood stream infections will be ill enough to be hospitalized; about 1% of children with blood stream

infections or pneumonia with a blood stream infection will die of their illness. Nearly all children with ear infections recover, although children with recurrent infections can suffer hearing loss.

Samples which can be used for Extraction: C.S.F. Bronchial Swabs, Bronchial lavage etc.

4. Precautions for PCR

The following aspects should always be taken care of:

- Store positive material (Specimens, Standards or amplicons) separately from all other reagents and add it to the reaction mix in a separate facility.
- Thaw all components thoroughly at room temperature before starting the assay.
- When thawed, mix the components and centrifuge briefly.
- Work quickly on ice or in the Cooling Block.
- All the reagents including the NTC (except for standards & specimens) should be mixed & dispensed in pre-mix area.
- All the standards & specimens should be mixed & dispensed in extraction area.
- Use pipette tips with filters only.
- Always use disposable powder-free gloves

5. Additionally Required Materials and Devices

- DNA isolation kit (see 8.a. DNA extraction)
- 0.2 ml PCR tubes for use with 36-well rotor (Corbett Research, Cat.-Nr.: SE-1003F) alternatively 0.1 ml PCR tubes for use with 72-well rotor (Corbett Research, Cat.-Nr.: ST-1001)
- Micro Pipettes Variable Volume 2-20µl, 10-100µl, 100-1000µl,
- Sterile pipette tips with aerosol barrier 2-20µl, 10-100µl, 100-1000µl,
- Disposable powder-free gloves
- Vortex mixer
- Centrifuge Desktop with rotor for 1.7 ml reaction tubes
- Rotor Gene[™] 2000,3000 or Rotor Gene[™] 6000, Corbett Research (The Real time PCR Instrument)

6. Principle of Real-Time PCR

The robust assay exploits the so-called Taqman principle. During PCR, forward and reverse primers hybridize to a specific sequence product. A TaqMan probe, which is contained in the same reaction mixture and which consists of an oligonucleotide labeled with a 5'-reporter dye and a downstream, 3'-quencher dye, hybridizes to a target sequence within the PCR product. A Taq polymerase which possesses 5' - 3' exonuclease activity cleaves the probe. The reporter dye and quencher dye are separated upon cleavage, resulting in an increase in fluorescence for the reporter. Thus, the increase in fluorescence is directly proportional to the target amplification during PCR.

7. Description Of the Product.

The **Geno-Sen's** Streptococcus pneumoniae *PCR* Reagents constitute a ready to use system for detection and quantification of Streptococcus pneumoniae using Polymerase chain reaction (PCR) in the Rotor Gene 2000/3000/6000 (Corbett Research). *The Specific Master* mix contains reagents and enzymes for the specific amplification of Streptococcus pneumoniae and for the direct detection of the specific amplicon in fluorescence channel Cycling A.FAM/Green of the *Rotor Gene 2000/3000/6000 & the Reference gene on* Cycling A. JOE/Yellow. External positive Standards (S. Pneumo. S 1-5) are supplied which allow the determination of the gene load. For further information, please refer to section 8.c Quantitation.

8. Procedure

8.a DNA Extraction

DNA Extraction kits are available from various manufacturers. Sample volumes for the DNA Extraction procedure depend on the protocol used. Please carry out the DNA Extraction according to the manufacturer's instructions. The recommended Extraction kits are the following:

Sample Material	Nucleic Acid Isolation Kit	REF Cat. Num.	••••
Serum or plasma.CS F,Bronchial	Geno Sen's [®] Genomic DNA Extraction Mini Kit — for DNA purification	98021 or 98022	Genome Diagnostics Pvt. Ltd. India
lavage,etc.	QIAamp Blood DNA Mini extraction Kit (50)	51104	QIAGEN
	Suitable Extraction kit which give a higher yield.		

Above Kits for evaluated in conjuction with the Geno Sen's[®] S.Pneumonia Real Time PCR RG Kit on the RotorGene 3000/6000.. However the sample size was limited for this study hence for all practical purposes all the validations were conducted with the Geno Sen's[®] Genomic DNA Extraction Mini Kit — for DNA purification

However the customer can use their own extraction systems depending on how good the yield is. Always use an extraction kit with a higher DNA yield.

Blood collection tubes coated with anticoagulants may inhibit the PCR, However these inhibitors will be eliminated by the use of the isolation kits given above. It is recommended to avoid the usage of heparin blood.

When using Extraction protocols with ethanol-containing washing buffers, please carry out an additional centrifugation step before the elution to remove any remaining ethanol. This prevents possible inhibition of PCR.

The Streptococcus pneumoniae *Rotor Gene PCR Reagents* should not be used with phenol based isolation methods.

8.b *Inhibition Control:*

Inhibition Control Gene allows the user to determine & control possible PCR inhibition. The Inhibition Control gene reagents are in built in the premix provided and need not be run separately. There is need to add internal control Gene in the reaction mix which has been provided as IC-1 RG (R3). To add the IC Gene 0.5 μ I/rxn of R3 is added to the premix as shown in the Figure 4 & 5. The results can be visualized in the Joe channel. . However if there is a need for the Internal control to be used as an extraction efficiency control, then 5 μ I of R3 i.e. Inhibition control should be added to each sample before adding the Buffer MBD in the extraction process.

However in such a case, the IC-1 (R3) should not be mixed with the pre-mix as described above & instead 0.5 μ I/rxn Molecular Grade water should be added to the pre-mix.


Also Note that in such a case there will be no amplification of Internal control in the Joe Channel in the NTC, & Standards. There will only be amplification in the Joe Channel in the Samples to which the IC-1 (R3) has been added before extraction.

Whereas if the IC-1 (R3) is added to the premix then there will be amplification in Joe Channel in all the samples, standards & NTC.

8.c Quantitation

The quantitation standards provided in the kit (*S.Pneumo. S 1-5*) are treated in the same way as extracted samples and the same volume is used i.e. (10µl) instead of the sample. To generate a standard curve in the *RotorGene*TM 2000/3000/6000, all 5 Standards should be used as defined in the menu window *Edit Samples* of the *RotorGene*TM software. The same should also be defined as standards with the specified concentrations (see *RotorGene*TM Manual). The standard curve generated as above can also be used for quantitation in subsequent runs, provided that at least one standard is used in the current run. For this purpose, the previously generated standard curve needs to be imported (see *Rotor Gene*TM 2000/3000/6000 Manual). However, this quantitation method may lead to deviations in the results due to variability between different PCR runs & due to varying Reaction efficiencies.

<u>Attention</u>: The standards are defined as Copies/µI. The following formula has to be applied to convert the values determined using the standard curve into Copies/mI of sample material:



Or else direct conversion can be done keeping in mind the starting volume of the sample & the final eluted Volume e.g.

If the starting volume of the sample while using the **Geno Sen's**[®] Genomic DNA Extraction Mini Kit is 200µl & the final Eluted Volume is 60µl then to obtain the direct values i.e. Copies/ml for the patient samples the following values for the standards can be fed directly into the operating software which is again based on the above formula and will yield direct conversion of per ml of patient sample data.

	10^5 Copies /µl =	30000000 Copies/ml
	10^4 Copies /µl =	3000000 Copies/ml
S3:	10^3 Copies /µl =	300000 Copies/ml
	10^2 Copies /µl =	30000 Copies/ml
S5:	10^1 Copies /µl =	3000 Copies/ml

If the starting volume of the sample while using the Qiagen QIAamp DNA Mini extraction kit is 200µI & the final Eluted Volume is 50µI then to obtain the direct values i.e. copies/mI for the patient samples the following values for the standards

can be fed directly into the operating software which is again based on the above formula and will yield direct conversion of per ml of patient sample data.

S1: 10 ⁵ Copies/μl =	25000000 Copies/ml
S2: 10^4 Copies /µl =	2500000 Copies/ml
S3: 10^3 Copies /µl =	250000 Copies/ml
S4: 10^2 Copies /µl =	25000 Copies/ml
S5: 10^1 Copies /µl =	2500 Copies/ml

8.d Preparation for PCR

8. e. Preparation for PCR amplification:

First make sure that the Cooling Block (accessory of the *Rotor Gene*TM, Corbett Research) is pre-cooled to +4°C in a Refrigerator or Deep Freezer. Place the desired number of PCR tubes into the Cooling Block. Make sure that the tubes for standards & at least one negative control (*Water, PCR grade*) are included per PCR run. To generate a standard curve, use all supplied Standards (*S. Pneumo. S 1-5*) for each PCR run. Before each use, all reagents need to be thawed completely and mixed (by pipetting or by brief vortexing).

Please follow the pipeting scheme mentioned below for each sample depending upon the number of samples a mix can be prepared as follows. Each sample




Fig. 4.

Depending upon the number of samples the following pipetting scheme can be followed. e.g. for 10 rxns.

Streptococcus pneumoniae MASTER MIX	1 rxns.	10 rxns.
Streptococcus pneumoniae Super Mix (R1)	12 μL	120 µL
Streptococcus pneumoniae Mg Sol. (R2)	2.5 µL	25 µL
IC-1 (R3) 1 µL	0.5 μL	5 µL
Total	15µL	150µL

Fig. 5.

Pipette 15 µl of the Master Mix into each labelled PCR tube. Then add 10 µl of the earlier extracted DNA to each sample tube and mix well by pipeting up and down. Correspondingly, 10 µl of the Standards (S. Pneumo *S1-5*) must be used as a positive control and 10 µl of water (*Water, PCR grade*) as a negative control. Close the PCR tubes and transfer the S. Pneumo tubes into the rotor of the *RotorGene*TM instrument. The *RotorGene*TM software versions 5.0.53 and higher require a Locking Ring (accessory of the *RotorGene*TM, Corbett Research) to be placed on top of the rotor to prevent accidental opening of the tubes during the run.

8.f. Programming the *RotorGene*[™] 2000/3000


The *RotorGene*[™] 2000/3000 PCR program for the detection of Streptococcus pneumoniae can be divided into following steps:

- A. Setting of general assay parameters & reaction volume
- B. Thermal Profile & Calibration
- C. Cycling profile/ & Initial activation of the Hot Start enzyme
- D. Cycling for Amplification of DNA
- E. Adjustment of the sensitivity of the fluorescence channels
- F. Starting of the Rotor Gene™ run

Program the *RotorGene*TM 2000/3000 for these 5 steps according to the parameters shown in Fig. 6-20. All specifications refer to the *RotorGene*TM software version 6.0.33. Please find further information on programming the *RotorGene*TM in the *RotorGene*TM 2000/3000 Operator's Manual,. In the illustrations these settings are shown by arrows

Setting of general assay parameters & Reaction volume.

First, confirm whether the PCR tubes used are No Domed PCR tubes by clicking in the box as shown in the figure. Please note that tubes with domes cannot be used in Rotor gene hence click in the box as shown below.



Confirmation of Reaction Volume as follows.




Fig. 7. Setting of general assay parameters.

- Please click on the volume buttons to make sure that 25µl is reflected in the window as shown above.
- Then click next and a new window will open as shown below.

THERMAL PROFILE & CALIBRATION:

Here the thermal profile for the assay will be defined.

💦 Rotor-Gene VIRTUAL MODE - Run 2006-05-17 (1)	_ B ×
<u>Eile Analysis Run Gain View Window Help</u>	
New Open Save Start Pause Stop Help View Settings Progress Profile Temp. Samples Analysis Reports Arrange	
Channels	
New Run Wizard	
	3 2 2 3 3 3 3 3 3 3 3 3 3 3 3 3
Rotor-Gene Analysis Software 6.0 (Build 33) VIRTUA	AL MODE
🤮 Statt 🛛 🖉 🥔 🖾 🚾 📴 🕲 🖙 🛬 🖲 鼷 🚿 📉 🔤 🖉 Yah 🕅 Boto 📉 Roto 🔤 🖏 🖏 🖓 🌚 🕁	🖗 6:03 PM
Fig. 8.	


Programming the temperature profile is done by activating the button *Edit Temperature Profile* in the next *New Experiment Wizard* menu window as shown above.

CYCLING PROFILE: First hold 95°C for 10 minutes as below

💦 Rotor-I	Gene VIRTUAL MODE - Run 2006-05-26 (1)	_ 8 ×
<u>F</u> ile <u>A</u> na	😰 Edit Profile 🛛 🔀	
New 0	New Open SaveAs Help	
Channel	The run will take approximately 105 minute(s) to complete. The graph below represents the run to be performed :	
	Click on a cycle below to modify it :	
	Hold Insert after	
	Insert before	
	Remove	
	Hold Temperature : 95 sc	
	Hold Time : 10 mins 0 secs	
	Rotor Speed : Norma Speed	
	\backslash	
		nk Off
	N N	All Off
Rotor-Ger	- 11	10DE 2-06 PM

Fig. 9. Initial activation of the Hot Start enzyme.

Setting up of denaturation step in the cycling profile as depicted below i.e.



95°C for 15 seconds.

Setting up of Anneling step in the cycling profile as depicted below i.e. 55°C for 20 Seconds and defining the Data acquiring channel i.e FAM & JOE






Fig. 11.

Setting up of Extension step in the cycling profile as depicted below i.e. $72^{\circ}C$

for 15 Seconds



Setting up of Number of Cycles to 45 cycles in the cycling profile as depicted below.



Final Confirmation of the Thermal profile by pressing OK button as shown

below.




Fig. 14.

Setting the gains for the acquiring channel by clicking at the Calibrate button as shown below.

<mark>▼ Rotor-Gene VIRTUAL MODE - Run 2006-05-20 (1)</mark> File Analysis Run Gain View Window Help	
	ange
Channels	
New Run Wizard	×
Image: Step Wigard Temperature Profile : Image: Step Wigard Temperature Profile : Image: Step Wigard This box difference Image: Step Wigard This box difference Image: Step Wigard Temperature Profile : Image: Step Wigard Create New Image: Step Wigard Create New Image: Step Wigard Create New Image: Step Wigard Create New	ments in 54 For help 3 hover 22 lo over the 22 lo, You 1 lick on a k to display 1 its
Rotor-Gene Analysis Software 6.0 (Build 33)	VIRTUAL MODE
] 🏽 Start 🛛 🥭 🗯 🔤 📴 🕲 🖙 🧽 👋 😡 Yaho] 🖙 Fung] 题] HIV] 🔩 Rotor 🖏 法条令 🔂	🔊 🗡 🖓 💕 5:22 PM 🛛

The detection range of the fluorescence channels has to be determined according to the fluorescence intensities in the PCR tubes. This adjustment is done in the menu window *Auto Gain Calibration*

Fig. 15.

Setup (activation in menu window *New Experiment Wizard* under *Calibrate*). Please set the calibration temperature to the annealing temperature of the amplification program (compare Fig. 16).

Adjustment of the fluorescence chann	el sensitivity as shown below.
--------------------------------------	--------------------------------

		- 111	TOPIC	MODE		2000 0	5-26 (1)									_
<u>File A</u>	ynalysis	<u>R</u> un	<u>G</u> ain	⊻iew	<u>₩</u> indov	v <u>H</u> elp										
Mew New	🤔 Open	∣ Save	Star) 🔵 se Stor		D	Setting	e Promess	Profile] Temn	;∲ Samples	Analusis		Arrange	
Chann	nels						ibration	Setup					×			
4				card	Chan FAN JOE	Calibrate Calibrate 'enform Ca 'enform Ca 'enform Ca 'enform Ca 'enform Ca 'enform Ca 'enform Ca	ferent gai coeptable. emistry yc et tempera All 1 alibration A alibration A 1 1 1	alibration win n levels unt The range us are perfor sture to 55 Calibrate Ac Before 1st A At 55 Decare sition Mii SFI SFI	il it finds or of fluoresc ming. deg equiring equisition es At Begi	nning Of R	n the fluore are looking		vels are	help o the wi on an your n item fo can a comb help a	IX took displays on elements in izard. For help item, hover nouse over the or help. You iso click on a o box to display about its bile settings.	Bani Dn jes
														_		
Rotor-G	iene An	alusis Si	oftware	6.0 (Bu	ild 331										IVIBIU	JAL MC
Rotor-G				`) 🖂 🗄	• •	»IG	u lea	r I 🔜 B	🖻 н		103		VIRTU 	JAL MO

Notor-Gene VIRTUAL MODE - Run 2006-05-26 (1) File Analysis Run Gain View Window Help	_ @ ×
New Dpen Save Start Period Store Help View Settings Profile Term Samples Analysis	Peports Arrange
New Dell Save Sale Sale Auto Sain Calibration Setup Channels Auto Gain Calibration will read the fluoresence on the inserted sample at acceptable. The range of fluorescence levels are acceptable. The range of fluorescence you are looking for depends on the chemistry you are performing. Set temperature to 55 # degrees. Calibrate All Calibration At 55 Degrees At Beginning Of Ruri Channel Settings Add Mame Tube Position Min Reading Edit FAM/Sybr 5FI 10FI Remove All Set merupet Close Element Merupet Close	This box displays help on elements in the wizard. For help on an item, hover your mouse over the tem for help. You can also click on a combo box to display help about its available settings.
Rotor-Gene Analysis Software 6.0 (Build 33)	
🏽 🚮 Start 🛛 💋 🥔 🖾 🔝 🔝 🖸 🕲 🖙 🍰 🕘 👋 🛄 J 🔄 T 💦 R 劑 H	🖳 🖸 🗡 🖓 覺 👘 7:16 PM 👘

Fig. 17.

Please do not forget to click on the box against "Perform calibration at 55°C at beginning of the run." After that press Close and a new window will open as shown below.

The gain values determined by the channel calibration are saved automatically and are listed in the last menu window of the programming procedure.

PRESS NEXT




Fig. 18.

Starting of the Rotor Gene™ run.

Rotor-Gene VIRTUAL MODE - Run 200 File Analysis Run Gain View Window H		<u>-8×</u>
New Open Save Start Pause Stop	Help View Settings Progress Profile Temp. Samples Analysis Reports Arrange	
Channels		-1
New Run Wizard	<u><</u>	
)5 04 03 02 01 01
	Setting Value FAM/Sybr Gain 8 JDE Gain 5 Auto-Calibration Before Run At 50 Degrees High Speed Rotor On Rotor 36-Well Rotor Sample Layout 1, 2, 3,	
	You are about to run in VIRTUAL mode. Once you've confirmed that your run settings are correct, click Start Run to Start Run to Start Run pegin the run. Skip Wizard < << Back	Bank Off Dn All Off es
Rotor-Gene Analysis Software 6.0 (Build 33)		UAL MODE
🏦 Start 🗹 🥭 🗐 🔣 👿 🖪 🕲 🛛	그 🎰 🔷 🔯 Yaho 🖂 Fung 👻 HIV 💦 Rotor 🔀 🧏 🍪 🤾 🚍 🚳 🗡 🎔	ቻ 5:26 PM

Fig. 19:

Press Start Run Button.

Save As	
	emp. Samples Analysis Reports Arrange
Demonstrations Export	
Log Archive	X
Reports Templates	3TD. PREP
File name: S.pneumonia 121205	
Save as type: Run File (*.rex)	i0
Setting Value FAM/Sybr Gain 10 JOE Gain 10 JOE Gain 10 Auto-Calibration Before Run At 55 Degrees High Speed Rotor On Rotor 36-Well Rotor Sample Layout 1, 2, 3,	
You are about to run in VIRTUAL Once you've confirmed that your run settings are com begin the run.	
Skip Wizard << Back	
Rotor-Gene Analysis Software 6.0 (Build 33)	VIRTUAL MODE
🏽 Start 🛛 🥖 🤌 🖾 🐨 📴 🕲 🛥 🔧 🔵 🗂 💩 🗍 💁 🕅	💦 В. 🛛 🛗 🍪 🥞 🍕 🧐 🚍 🧐 🖓 😭 6:27 РМ

Fig. 20.

SAVING THE RUN FILE AS ABOVE

Store the run file either in my documents or a designated folder as shown above. The moment save button is clicked after the file name, machine will start.

8.g. Programming the *RotorGene*[™] 6000


The *RotorGene*[™] 6000 PCR program for the detection of *Streptococcous Pneumonia* can be divided into following steps:


- G. Setting of general assay parameters & reaction volume
- H. Thermal Profile & Calibration
- I. Cycling profile/ & Initial activation of the Hot Start enzyme
- J. Cycling for Amplification of DNA
- K. Adjustment of the sensitivity of the fluorescence channels
- L. Starting of the Rotor Gene™ run

Program the *RotorGene*TM 6000 for these 5 steps according to the parameters shown in Figures 21-37 below All specifications refer to the *RotorGene*TM 6000 software version 1.7 Please find further information on programming the *RotorGene*TM in the *RotorGene*TM 6000 *Operator's Manual*,. In the illustrations these settings are shown by arrows

g) Setting of general assay parameters & Reaction volume.

Please see to it that you in advanced mode and then click Hydrolysis Probes. On a double click the software will automatically go to the next function. If there is just a single click then click new after highlighting the Hydrolysis Probes.





First, confirm by clicking in the box as shown in the figure above whether a locking ring has been attached. Then click next to proceed to the next step.

Series Software VIRTUAL MODE - Run 2008-07-27 (1) New Open Save Start Pause Stop View 🔗 🛑 🗗 🚺 🍋 👫 Ei 🗖 -Help New Run Wizard This screen displays miscellaneous options for the run. Completicity of the next page. Operator : PETER S. PNEUMONIA QUANTITATION Notes : 25 Reaction Volume (µL): Sample Layout : 1, Skip Wizard << <u>B</u>ack <u>N</u>ext>> 24 Bank On Bank Off Named On All On All Off Edit Samples... Rotor-Gene 6000 Series Software 1.7 (Build 40) *by start b* VIRTUAL MODE

Confirmation of reaction Volume as follows.

Fig. 23.

- Please click on the volume buttons to make sure that 25µl is reflected in the window as shown above.
- In case required Operators Name can be Fed into the system.
- Any Notes which need to be either printed into the Report can be typed out in the Box of Notes.
- Then click next and a new window will open as shown below.

h) THERMAL PROFILE & CALIBRATION:

Here the thermal profile for the assay will be defined.

😫 Rotor-G	ene 600	0 Serie:	s Softw	are VII	RTUAL MC	DE - H	ydrolysis	Probes	2007-0	7-03 (1)					_ 8 ×
<u>File</u> <u>Analys</u>	sis <u>R</u> un	<u>G</u> ain <u>N</u>	√iew <u>∖</u>	/indow	<u>H</u> elp										
Mew Ope	n Save) Start	Pause	Stop	3 Help	View	्रु Settings P/	O gress	Profile	📕 Temp.	Samples	knalysis	Reports	Arrange	
Channels	New R													×	d.
1	New R	un Wiza	ard	_	Temperatur	e Profile							TT1 - 1	x displays	
			00000		Edit Profil Channel Se Green Yellow Orange Red Crimson Gain <u>Optim</u>	e Source 470nm 530nm 530nm 625nm 680nm	Detecto 510nm 5510nm 660nm 10hp	r Gair 5 5 5 7			E	ate <u>N</u> ew Edit dit <u>G</u> ain <u>R</u> emove et <u>D</u> efaults	help or the wiz on an i your m item for can als combo help at availab	elements in ard. For help tem, hover ouse over the help. You to click on a box to display	Bank Off
	1		∞ 🎖	$\mathbb{R}^{\mathbf{r}}$	Skip Wiz	ard 1	<< Back	1	Next >>	1					es
			~ ^		erop with		<u>P</u> dok		<u></u>		_	_]
Rotor-Gene	6000 Serie	es Softwa	are 1.7 (B	uild 40)										,	AL MODE
🛃 Start	🧭 💋	🗯 🗖	1 🖻 🖥	•	🖪 🥅 🍯) 🕥	2		BEAL .	🖻 н	BV •	g Rotor	. 83	≝∎ ∢⊛ (11:26 AM
Fig. 2	24.														

Programming the temperature profile is done by activating the button *Edit Profile* in the next *New RUN Wizard* menu window as shown above.

i) CYCLING PROFILE: First hold 95°C for 10 minutes as below





Fig. 25. Initial activation of the Hot Start enzyme. Generally the window will open with the Hold Temp as 95°C and the Hold Time as 10 minutes. In case it is different then set the same to as shown above.

j) Setting the Cycling and acquisition.

When clicked on Cycling the window will open as below.




Click on the Plus sign at the right hand as shown in the figure to make the Cycling a three step process. A new window as shown below will be there.

Setting up of denaturation step in the cycling profile as depicted below i.e. 95°C for 15 seconds.

ዿ Rotor-I	Gene 6000 Series Software VIRTUAL MODE - Hydrolysis Probes 2007-07-03 (1)	_ 8 ×
<u>File A</u> na	📲 Edit Profile 🛛 🗙	
Mew O	New Open Save As Help	
Channel	The run will take approximately 100 minute(s) to complete. The graph below represents the run to be performed :	
	Click on a cycle below to modify it :	
	Hold Insert after	
	Insert before	
	Remove	
	This cycle repeats 40 time(s).	
	Click on one of the steps below to modify it, or press + or - to add and remove steps for this cycle.	
	Timed Step 95%C for 15 secs	
	15 seconds	
	Not Acquiring 72tC for 20 secs	
	Long Range 60°C for 45 secs	▶ ank Off
	Touchdown	All Off
Rotor-Ger		10DE
	- 1	
🚮 Start		1:27 AM
	Fig. 27.	

Setting up of Anneling step in the cycling profile as depicted below i.e. 55°C for 20

Seconds



After setting the Anneling temperature and the time for anneling click on the "Acquiring to Cycling A" as shown by arrow. A New window will open as shown below.

😫 Rotor-	Gene 6000 Serie	es Softwa	re VIRTI	JAL MODE	- Hydrolysis Probes 2007-07-03 (1)		<u>_ 8 ×</u>
<u>File</u> <u>A</u> na	📶 Edit Profile					×	
Mew O	May New Op	en Save	As He	a) elp			
Channel	The run will take	Acquisitio	on				
]		Same as F	revious :	(New Acqu	isition)		
			on Configu				
		Available	Channels	:	Acquiring Channels :	לולולולולור	
		Name Crimsor			Name Green	laaaaaa	
	Click on a cycle t Hold	Orange					
	Cycling	Red Yellow			<<		
					ect it from the list in the left and click >. To stop acquiring from a		
	This cycle repeat	channel,	select it ir	n the right-ha	nd list and click <. To remove all acquisitions, click <<.		
	Click on one of th						
	Timed Step	Dye Cha	t>> [UK Don't Acquire Help	· •	
	55º			ection Cha		/	
	20 sec			Detector			
	Acquiring to	Green	470nm	510nm		secs/	
	on Gr	Yellow	530nm	555nm	JOE [®] , VIC [®] , HEX, TET [®] , CAL Fluor Gold 540 [®] , Yakima Yellow [®]		ank Off
	Long Range	Orange	585nm	610nm	R0X ¹ , CAL Fluor Red 610 ¹ , Cy3.5 ¹ , Texas Red ¹ , Alexa Fluor 568 ¹		All Off
		Red	625nm	660nm	Cy5 ¹), Quasar 670 ¹), LightCycler Red640 ¹), Alexa Fluor 633 ¹		
		Crimson	680nm	710hp	Quasar705 ¹), LightCycler Red705 ¹), Alexa Fluor 680 ¹		
	_						
Rotor-Ger						<u>o</u> k	IODE
🄀 Start	🧭 🧶 🚺	- 🖬 👿	X 🖪) 🔤 🥌 (🕲 😤 🔰 🔄 REAL 🖄 HBV 📓 Rotor 🛛 🖽	23 - 	1:29 AM
					Fig. 29.		

Defining the Data acquiring channel i.e Green (FAM) & Yellow (JOE)


Highlight the Yellow and then press the right arrow. Just see before shifting the yellow to right that there is no other channel in the right except for Green. In case any other Channel appears besides Green on the right then the same be shifted to the left.

Carl I		es Softwa	re VIRTI	JAL MODE	- Hydrolysis Probes 2007-07-03 (1)		<u>_ 8 ×</u>
<u>File A</u> na	🖬 Edit Profile					×	
1	Ø 🚺	- 0.0)			
New O	New Op The run will take	ien Save		elp		L	
Channel	The run will take						
-		Same as F	revious :	(New Acqui	isition)		
			on Configu				
		Available	Channels	::	Acquiring Channels :	ולולולולולורור	
	I	Name			> Name	րողողո	
	Click on a cycle t	Crimsor Orange			Green		
	Hold Cycling	Red			< <		
	C) CHILD						
	, This cycle repeat				ect it from the list in the left and click >. To stop acquiring from a nd list and click <. To remove all acquisitions, click <<.		
	Click on one of th	channoi,	SCICCUL	r the light he	na istana ciet (, referitore al acquisitori, ciet ().		
	le						
	Timed Step	Dye Cha	t>> 1		OK Don't Acquire Help	• •	
	55º			ection Cha		1	
	20 sec	<u> </u>		Detector		/	
	Acquiring to	Green	470nm	510nm		secs /	
	on Gr	Yellow		555nm	FAM ¹ , SYBR Green 1 ¹ , Fluorescein, EvaGreen ¹ , Alexa Fluor 488 ¹		►
	🔲 Long Range		530nm		JOE [®] , VIC [®] , HEX, TET [®] , CAL Fluor Gold 540 [®] , Yakima Yellow [®]		ank Off
	Touchdown	Orange	585nm	610nm	ROX ³ , CAL Fluor Red 610 ³ , Cy3.5 ³ , Texas Red ³ , Alexa Fluor 568 ³		All Off
		Red	625nm	660nm	Cy5 ^D , Quasar 670 ^D , LightCycler Red640 ^D , Alexa Fluor 633 ^D		
		Crimson	680nm	710hp	Quasar705 ¹), LightCycler Red705 ¹), Alexa Fluor 680 ¹		
	1 1						
Rotor-Ger						<u>0</u> K	IODE
🚮 Start	🧭 🍮 🚺	- 🖻 👿	× 🖪	📃 🙆 (🕲 🐁 🔰 🔄 REAL 💆 HBV 📓 Rotor 🛛 📆	9. * O * -	11:29 AM
					Fig. 30.		


Confirmation of Channels as shown below.

Once the Yellow and Green Channels are on the Right side then press OK as shown by the arrow.

Setting up of Extension step in the cycling profile as depicted below i.e. 72°C for 15 Seconds



Setting up of Number of Cycles to 45 cycles in the cycling profile as depicted below.



After setting the number of Cycles Press OK.

k) Setting the gains for the acquiring channel by clicking at the Gain Optimisation button as shown below.




Fig. 33


The detection range of the fluorescence channels has to be determined according to the fluorescence intensities in the PCR tubes. This adjustment is done in the menu window *Auto Gain optimization Setup* (activation in menu window *New Experiment Wizard* under Gain Optimization). Please set the temperature to the annealing temperature of the amplification program (compare Fig.34.

😫 Rotor-Gene 6000 Series Software VIRTUAL MOI)E - Hydrolysis Probes	: 2007-07-03 (1)		_ @ ×
<u>Eile Analysis R</u> un <u>G</u> ain <u>V</u> iew <u>W</u> indow <u>H</u> elp				
Image: Steam of the state of the s	View 🧬 🍵	1 👔 🕅) X	Arrange
Auto-Gain Optimisation Se	tup		×	1
New Run W New Run W	els until it finds one at which range of fluorescence you performing. o 55 degrees. ise Acquiring re 1st Acquisition	······	9	x displays relements in ard. For help tem, hover buse over the help. You o click on a box to display out its le settings. Bark Off Di S
Rotor-Gene 6000 Series Software 1.7 (Build 40)				VIRTUAL MODE
🎉 Start 🛛 💋 🥔 🧊 🖬 🔣 🖾 🥮 🥯	1- <u> </u>		BRotor	🕞 📕 🔍 🚱 🏹 11:32 АМ.
	Fig. 3	34.		


The following needs to be done.

- Click on the Optimise Acquiring
- Click on Set temperature To Adjust the Temperature to 55°C.
- Click on the Box Perform Optimisation At 55 degree At beginning of Run.
- Just see that below the channel settings there appear only two channels i.e. Green and Yellow. In case it is different then the channels have not been set properly. Close the window and reset the channels.
- Then Press Close.

L) PRESS Start RUN



Saving the RUN File.



Store the run file either in my documents or a designated folder as shown above. The moment save button is clicked after the file name, machine will start.

9. a) Generated Data Interpretation & Analysis For Rotor Gene 2000/3000

Data analysis is performed with the *RotorGene*[™] software according to the manufacturer's instructions (*RotorGene*[™] 3000 Operator's Manual).

The following results are possible:

1. A signal is detected in fluorescence channel Cycling A.FAM.

The result of the analysis is positive: The sample contains **Streptococcous Pneumonia** DNA.

2. In fluorescence channel Cycling A.FAM no signal is detected.

No Streptococcous Pneumonia DNA detectable. It can be considered negative if there is amplification in the Joe Channel. Please refer for details on PCR inhibition in the section PCR inhibition.




Fig. 37: Detection of the quantitation standards (**Streptococcous Pneumonia** *S 1-5*) in fluorescence channel Cycling A.FAM. NTC: non-template control.

Examples of positive and negative PCR reactions are given in the above figure.




Fig. 38.

Example of analysed data for Streptococcous Pneumonia where all the amplification curves can be seen as well as the standard curve, reaction efficiency, M value etc. can be seen and the quantitative data for the samples can be seen.

Inhibition Control gene amplification.

Analyze the Joe Channel

PCR Inhibition

A signal is detected in fluorescence channel Cycling A. Joe: No PCR inhibition

In fluorescence channel Cycling A. Joe no signal is detected.

But signal detected in FAM: The sample is positive for Streptococcous Pneumonia DNA.

In fluorescence channel Cycling A. Joe no signal is detected.

No signal detected in FAM as well: A possible PCR inhibition has occurred.

9. b) Generated Data Interpretation & Analysis For Rotor Gene 6000

Data analysis is performed with the *RotorGene*[™] software according to the manufacturer's instructions (*RotorGene*[™] 6000 Operator's Manual).

The following results are possible:

3. A signal is detected in fluorescence channel Cycling A.Green.

The result of the analysis is positive: The sample contains **Streptococcous Pneumonia** DNA.

4. In fluorescence channel Cycling A.Green no signal is detected.

No Streptococcous Pneumonia DNA detectable. It can be considered negative if there is amplification in the Yellow Channel. Please refer for details on PCR inhibition in the section PCR inhibition.




Fig. 39: Detection of the quantitation standards (**Streptococcous Pneumonia** *S* 1-5) in fluorescence channel Cycling A.Green. NTC: non-template control.

Examples of positive and negative PCR reactions are given in the above figure.




Fig. 40.

Example of analysed data for Streptococcous Pneumonia where all the amplification curves can be seen as well as the standard curve, reaction efficiency, M value etc. can be seen and the quantitative data for the samples can be seen.

Inhibition Control gene amplification.

Analyze the Yellow Channel

PCR Inhibition

A signal is detected in fluorescence channel Cycling A. Yellow: No PCR inhibition

In fluorescence channel Cycling A. Yellow no signal is detected.

But signal detected in Green: The sample is positive for Streptococcous Pneumonia DNA.

In fluorescence channel Cycling A. Yellow no signal is detected.

No signal detected in Green as well: A possible PCR inhibition has occurred.

10. a) Troubleshooting

For Rotor Gene 2000/3000

1. No signal with positive Standards (Streptococcous Pneumonia *S* 1-5) in fluorescence channel Cycling A.FAM.

- Incorrect programming of the *Rotor-Gene*[™] 2000/3000.
 - ➔ Repeat the PCR with corrected settings.

2. Weak or no signal in fluorescence channel Cycling A. FAM:

- The PCR conditions do not comply with the protocol.
 - → Repeat the PCR with corrected settings.
- The **Streptococcous Pneumonia** Super Mix *R1* has been thawed and frozen too often.
- The **Streptococcous Pneumonia** Super Mix R1 has been kept at +4°C for longer than 5 hours.
 - → Please mind the storage conditions given in the **Storage**.
 - → Repeat the assay using a new Streptococcous Pneumonia super mix (R1).
- The PCR was inhibited.
 - Make sure that you use a recommended extraction method (see 8.a. DNA extraction) and stick closely to the manufacturer's instructions.

10. b) Troubleshooting

For Rotor Gene 6000

1. No signal with positive Standards (Streptococcous Pneumonia *S 1-5*) in fluorescence channel Cycling A.Green.

- Incorrect programming of the *Rotor-Gene*[™] 6000.
 - ➔ Repeat the PCR with corrected settings.

2. Weak or no signal in fluorescence channel Cycling A. Green:

- The PCR conditions do not comply with the protocol.
 - → Repeat the PCR with corrected settings.
- The **Streptococcous Pneumonia** Super Mix *R1* has been thawed and frozen too often.
- The Streptococcous Pneumonia Super Mix R1 has been kept at +4°C for longer than 5 hours.
 - → Please mind the storage conditions given in the **Storage**.
 - → Repeat the assay using a new Streptococcous Pneumonia super mix (R1).

• The PCR was inhibited.

→ Make sure that you use a recommended extraction method (see 8.a. DNA extraction) and stick closely to the manufacturer's instructions.

11. Specifications

11.a Sensitivity and Reproducibility

In order to determine the sensitivity of the *Geno-Sen's* Streptococcous **Pneumonia** *Real Time PCR Kit*, a dilution series has been set up from 10^7 down to 10^0 Copies/µl of Streptococcous Pneumonia DNA and analyzed with the *Geno-Sen's* Streptococcous Pneumonia *Real Time PCR Kit*. The assays were carried out on three different days in the form of 8-fold determinations. The results were determined by a probit analysis. The detection limit as determined for *Geno-Sen's*

Streptococcous Pneumonia Real Time PCR Kit is consistently 80 copies/ml. This

means that there is 95% probability that 80 copies/ml will be detected.

Analytical Sensitivity

Analytical Sensitivity in Conjunction with the Geno Sen's[®] Genomic DNA Extraction Mini Kit — for DNA purification (Cat . No. 98021) of the Geno Sen's[®] Streptococcous Pneumonia Real Time PCR RG Kit on RotorGene 3000/6000 was determined by Spiking a known negative Serum to a nominal 80 copies/ml. This was subjected to extraction using the Geno Sen's[®] Genomic DNA Extraction Mini Kit — for DNA purification (Cat . No. 98021) eight times with starting volume of 200µl & elution volume of 60µl.

All the Eight extractions were then analyzed with the Geno Sen's[®] Streptococcous Pneumonia Real Time PCR RG Kit along with the standards & the NTC.

All the eight extractions were amplified correctly & the mean value obtained for the eight replicates was 79 copies/ml.

Hence Analytical Sensitivity in Conjunction with the Geno Sen's.[®] Genomic DNA Extraction Mini Kit — for DNA purification (Cat . No. 98021) of the Geno Sen's[®] Streptococcous Pneumonia Real *Time PCR RG Kit on RotorGene 3000/6000 was determined to be 80 copies/ml*

11.b Specificity

In order to check the specificity of the *Geno-Sen's* Streptococcous Pneumonia Real Time PCR kit, different DNA & RNA listed below were analyzed with *Geno-Sen's* Streptococcous Pneumonia Real Time PCR Kit. None of these led to a positive signal with the *Geno-Sen's* Streptococcous Pneumonia Real Time PCR kit. Gene sequence analysis of the amplified region of Streptococcous Pneumonia shows a pronounced homology among the various Streptococcous Pneumonia subtypes, and no homology with other DNA. Besides which utmost care has been taken in selection of the primers & probes being used in the kit.

To further Validate the stringent data In order to check the specificity of the *Geno Sen's*[®] **Streptococcous Pneumonia** *Real Time PCR RG Kit*, different RNA & DNA listed below were analyzed with *Geno Sen's*[®] **Streptococcous Pneumonia** *Real Time PCR RG Kit*. None of these led to a positive signal with the *Geno Sen's*[®] **Streptococcous Pneumonia** *Real Time PCR RG Kit*.

Vericella Zoster Virus	TTV	N. Meningitis
Human Herpes Virus 6	Hepatitis C Virus	ChikunGunya Virus
Epstein barr Virus	Hepatitis E Virus	ENTEROVIRUS
Cytomagalovirus	HIV-1	Mycobacterium tuberculosis
H. Pylori	HIV-2	Hepatitis A
Parvovirus B 19	WEST NILE VIRUS	Staphylococcus aureus
Dengue Virus 1-4	H. Influenza	Salmonella enteritidis
Leprosy	Malaria	Scrub typhus
B.pseudomallie	JEV	Leptospira interrogans.

In order to validate the Specificity further with wet lab testing the following Known clinical samples were analyzed using the *Geno Sen's.[®]* Streptococcous **Pneumonia** Real Time PCR RG kit on RotorGene 3000/6000. The extraction was carried out with the Geno Sen's[®] Genomic DNA Extraction Mini Kit — for DNA purification (Cat. No. 98021)

The run was carried out with the known set of standards in order to quantiate the **Streptococcous Pneumonia** Gene.

Sample Type	CSF	BRONCHIAL LAVAGE
High +ve's	4	
Medium +ve's	4	3
Low +ve's	7	5
Extremely low +ve's	3	2
Negative samples.	6	4
	24	14

All the above samples were correctly identified by the *Geno Sen's*[®] Streptococcous **Pneumonia** Real Time PCR RG kit & all the 6 extremely low samples were accurately detected by the *Geno Sen's*[®] Streptococcous Pneumonia Real Time PCR RG kit & exhibited copies around 80 copies /ml or less than 80 copies/ml.

Further studies are underway on this aspect.

12. Warranty::

Products are guaranteed to confirm to the quality and content indicated on each vial and external labels during their shelf life. Genome Diagnostics Pvt. Ltd. obligation and purchaser's rights under the warranty are limited to the replacement by Genome Diagnostics Pvt. Ltd of any product that is shown defective in fabrication, and that must be returned to Genome Diagnostics Pvt. Ltd Freight prepaid, or at Genome Diagnostics Pvt. Ltd. option, replacement of the purchasing price. Any complaint on damaged goods during transport must be directed to the handling or transport agent.

In Vitro Diagnostic Medical device, as per the Directive 98/79/EC specifications. This product must be used by qualified professionals only. It is the responsibility of the user to ascertain that a given product is adequate for a given application. Any product not fulfilling the specifications included in the product sheet will be replaced. This warranty limits our responsibility to the replacement of the product. No other warranties, of any kind, express or implied, including without limitation, implicit warranties of commercialization ability or adequacy for a given purpose, are provided by Genome Diagnostics Pvt. Ltd. Genome Diagnostics Pvt. Ltd will not be responsible for any direct, indirect, consequential or incidental damage resulting of the use, misuses, results of the use or inability to use any product.

13. Limitations of product use:

- a.) All reagents may exclusively be used for *in vitro* diagnostics.
- b.) The product is to be used by personnel specially instructed and trained in for the *in-vitro* diagnostics procedures only.
- c.) It is important to pipet the indicated quantities, and mix well after each reagent addition. Check pipettes regularly.
- d.) Instructions must be followed Correctly in order to obtain correct results. If the user has any questions, please contact our Technical Dept. (<u>dharam@vsnl.com</u> or at pbpl@vsnl.net).
- e.) This test has been validated for use with the reagents provided in the kit. The use of other Reagents or methods, or the use of equipment not fulfilling the specifications, may render equivocal results. User is responsible for any modifications done in any of the indicated parameters. Compliance with the kit protocol is required.
- f.) Detection of bacterial DNA depends on the number of DNA present in the sample, and can be affected by sample collection methods, patient-related factors (e.g. age, symptoms), or for infection stage and sample size.
- g.) False negative results may be obtained due to polymerase inhibition. It is recommended to perform control reactions to distinguish between inhibition and true negatives. This is achieved by the inhibition Control included in the kit.
- h.) Cross contamination between samples and exogenous DNA can only be avoided by following good laboratory practice. Instructions in this document must be strictly followed.
- i.) Attention should be paid to expiration dates printed on the kit box and labels of all components. Do not use expired components.

If you have any further questions or problems, please contact our technical support at <u>dharam@vsnl.com</u> OR <u>pbpl@vsnl.net</u>.

14. LIST OF GENO-SEN'S RANGE OF REAL TIME PCR KITS

S.NO.	PRODUCT
1	HIV-1 RG quantitative Real time PCR kit.
2	HBV RG quantitative Real time PCR kit.
3	HCV RG quantitative Real time PCR kit.
4	HCV Genotyping 1/2/3/4 RG qualitative Real time PCR kit.
5	HEV RG quantitative Real time PCR kit.

6	HAV RG quantitative Real time PCR kit.
7	JEV RG quantitative Real time PCR kit.
8	ENTEROVIRUS RG quantitative Real time PCR kit.
9	DENGUE RG quantitative Real time PCR KIT
10	HSV 1 & 2 RG quantitative Real time PCR kit.
11	CMV RG quantitative Real time PCR kit.
12	Hanta Virus RG quantitative Real time PCR kit.
13	Measles Virus RG quantitative Real time PCR kit.
14	West Nile Virus RG quantitative Real time PCR kit.
15	H5 N1 (Bird Flu) RG quantitative Real time PCR kit.
16	Chikungunya RG quantitative Real time PCR kit.
17	TTV RG quantitative Real time PCR kit.
18	SARS RG quantitative Real time PCR kit.
19	JC/BK Virus RG quantitative Real time PCR kit.
20	MTb Complex RG quantitative Real time PCR kit.
21	MTb Complex /MOTT RG quanlitative Real time PCR kit.
22	Chlamydia pneumonia RG quantitative Real time PCR kit.
23	Streptococcous pneumonia RG quantitative Real time PCR kit.
24	N. Meningitis RG quantitative Real time PCR kit.
25	H. Influenza RG quantitative Real time PCR kit.
26	Leprosy RG quantitative Real time PCR kit.
27	Helicobacter Pylori RG quantitative Real time PCR kit.
28	Scrub Typhus RG quantitative Real time PCR kit.
29	B. Pseudomalie RG quantitative Real time PCR kit.

30	Filaria RG quantitative Real time PCR kit.
31	Leptospira(pathogenic) RG quantitative Real time PCR kit.
32	CCL3-L1 RG quantitative Real time PCR kit.
33	Malaria (P. Vivax) RG quantitative Real time PCR kit.
34	Bcr/abl Major RG quantitative Real time PCR kit.
35	Bcr/abl Minor RG quantitative Real time PCR kit.
36	PML/RARA RG quantitative Real time PCR kit.
37	RARA/PML RG quantitative Real time PCR kit.
38	GAPDH RG quantitative Real time PCR kit.
39	β -Actin RG quantitative Real time PCR kit.
40	β -Globin RG quantitative Real time PCR kit.
41	Abl gene RG quantitative Real time PCR kit.
42	Rabies RG quantitative Real time PCR kit.
43	Factor V Leiden detection RG Real time PCR kit.

GENOME DIAGNOSTICS PVT. LTD. (AN ISO 13485 :2012,9001 : 2008 CERTIFIED COMPANY.) Up Mohal Naryal, KHASRA NO : 427, Opp. Divya Packers. Old Timber Depot Road, Near Sector 4, Parwanoo Distt. Solan, Himachal Pradesh-173220, INDIA. Tel No : 00-91-1792-234285, +91 9810037653 Fax : 00-91-1792-234286 E-mail: genome24@rediffmail.com dharam@vsnl.com pbpl@vsnl.net Version: 005 Websites : www.genomediagnostics.in www.genome-diagnostics.com www.genomediagnostics.co.in www.diagnosticsgenome.com



EMERGO EUROPE Prinsessegracht 20, 2514 AP , The Hague The Netherlands